

PowerMic Buttons and Functionality

Button	Function
Press-and-hold (Also known as the Dictation button)	Allows the microphone to begin actively listening to dictation. PowerMic II or III: Press and hold to dictate and release the button to stop. PowerMic Mobile: Press once to turn on and press once to turn off.
Previous Field	Moves to the previous set of brackets [].
Next Field	Moves to the next set of brackets [].
Accept Defaults	Removes all brackets from the given Auto-text and keeps any defaulted text that remains in the brackets.
Show/Hide Dictation Box	Will show the Dictation Box with one press and hide it when pressed again.
Transfer Text	Once the cursor is placed in the target text field, pressing this button will transfer the content of the Dictation Box to that target field.

PowerMic II or III

1 Previous Field

2 Transfer Text

3 Next Field

4 Press-and-hold

5 Recall Text

6 <None>

7 Show/Hide Dictation Box

8 <None>

9 Accept Defaults

10 <None>

PowerMic Mobile

1 Transfer Text

2 Accept Defaults

3 <None>

4 Previous Field

5 Press Hotkey

F3